



CPS160PBURC1 MOBILE POWER INVERTER



Offering household power on the go

The CyberPower 160 Power Inverter (CPS160PBURC1) converts power from your vehicle's 12V DC power outlet to household AC power to simultaneously power two devices with its one AC household outlet and a 2.4-Amp USB port.

The CyberPower 160 features a pivoting DC plug to fit into tight spaces in your vehicle and a 15-Amp fuse for over-current protection. It also provides surge protection and automatic power shutdown protect your connected devices from damaging surges and your automotive battery from power drain.

A Two-Year Warranty ensures that this product has passed our highest quality standards in design, assembly, material and workmanship.

TYPICAL APPLICATIONS

- Tablets
- Laptops
- Smartphones

FEATURES

- 160W Power Inverter
- 150° Swivel Head
- (1) USB 2.4 Amp Charging Port
- (1) 120Vac Outlet
- 2-Year Warranty

SPECIFICATIONS

INPUT	
Voltage	10.5Vdc - 15.5Vdc
Current	15A max
Plug Type	12Vdc Auto Power Port
Plug Style	150° Swivel Head
OUTPUT	
Watts - Continuous	100
Watts - Peak	160
On Battery Voltage	120Vac
On Battery Frequency	60Hz
On Battery Waveform	Simulated Sine Wave
Outlets - Total	1
Outlet Type	NEMA 5-15R
USB Charge Port - Total	1
USB Charging Amperage	2.4A

PROTECTION FEATURES	
Low Battery Voltage Shutdown	<11Vdc
High Battery Voltage Shutdown	>15Vdc
High Temp Shutdown	Yes
Overload Shutdown	Yes
INDICATORS	
Power	Green
Fault	Red
PHYSICAL	
Dimensions (WxHxD) (in.)	2.54 x 1.43 x 5.38
WARRANTY	
Product Warranty	2 Years Limited