

browning® NMO VHF Antennas

- Gold plunger type contact pin • Premium coil with metal base and top • 200 watts power rating
- Stainless steel tapered whip .100" (2.5mm) • Poly bag w/header card, UPC coded

NMO VHF 3 dBd Antennas

Model	Description	Frequency	Gain	Whip
BR-190 BR-190-S	5/8 wave w/spring	144-174 MHz	3 dBd	49" .100"(2.5mm)
BR-160 BR-160-S	5/8 wave w/spring	144-174 MHz	3 dBd	49" .100"(2.5mm)
BR-162	5/8 wave	200-260 MHz	3 dBd	37" .100"(2.5mm)

NMO No-Ground Plane 2.4 dBd Gain, 5 MHz Band Width

BR-165 BR-165-S	1/2 wave w/spring	132-174 MHz	2.4 dBd	49 7/16" .100"(2.5mm)
--------------------	----------------------	-------------	---------	-----------------------

NMO Wideband : 24 MHz VHF / 100 MHz UHF

BR-161	1/4 wave	132-970 MHz	Unity	19 3/4" .100"(2.5mm)
--------	----------	-------------	-------	----------------------

NMO UHF Antennas

- Gold plunger type contact pin • Premium coil with metal base and top • 200 watts power rating
- Stainless steel tapered whip .100" (2.5mm) • Poly bag w/header card, UPC coded

Model	Description	Frequency	Gain	Height
BR-173	5/8 over 5/8 wave	450-470 MHz	5.5 dBd	35"
BR-173-A	5/8 over 5/8 wave	406-430 MHz	5.5 dBd	35"
BR-173-B	5/8 over 5/8 wave	430-450 MHz	5.5 dBd	35"
BR-173-D	5/8 over 5/8 wave	470-490 MHz	5.5 dBd	35"
BR-173-E	5/8 over 5/8 wave	490-512 MHz	5.5 dBd	35"
BR-173-S	w/spring	450-470 MHz	5.5 dBd	33 1/4"
BR-177	5/8 over 1/2 wave	445-470 MHz	4.5 dBd	31"
BR-174	5/8 wave	450-470 MHz	3 dBd	10 3/4"
BR-176-S	5/8 wave w/spring	450-470 MHz	3 dBd	13"

NMO No-Ground Plane - 20 MHz Band Width

BR-175	1/2 wave	430-490 MHz	2.4 dBd	11 1/2"
--------	----------	-------------	---------	---------

NMO Amateur Dual Band Antenna

- Wide band • Pre Tuned • NMO mounting

BR-180	1/2 wave 5/8 over 5/8 wave	144-148 MHz 430-450 MHz	2.4 dBd 5.5 dBd	37 1/2"
--------	-------------------------------	----------------------------	--------------------	---------

NMO 800-900 MHz Antenna

- Wideband • Pre Tuned • NMO mounting

BR-800	5/8 over 1/4 wave	800-900 MHz	3 dBd	11 1/2"
--------	-------------------	-------------	-------	---------

NMO Low Band Antenna

- DC ground • Shunt fed base load • Can be used on magnet

Model	Description	Frequency	Gain	Whip
BR-140	1/4 wave	26.5-30 MHz	Unity	49" .100"(2.5mm)

