

# LOREX<sup>®</sup>

## Fusion 4K Network Video Recorder



### Product Specifications

#### General

Video Transmission Technology	IP
Channels	16 Channels / Lorex Fusion Wi-Fi

#### Inputs/Outputs

Video Input	8 x PoE, 8 x Lorex Fusion Wi-Fi
Video Outputs <sup>7</sup>	1 x VGA/1 x HDMI
Audio Input	1 x RCA
Audio Output	1 x RCA

#### Display

Display Output Resolution	Up to 4K UHD
Live Display	1,4,8,9,16
OSD	On/Off
System Navigation	USB Mouse

#### Recording

Recording Resolution	4K (8MP)/5MP/4MP/3MP/1080p/720p
Recording Frame Rate	4K (8MP)@15fps/5MP@30fps/4MP@30fps/1080p@30fps/720p@30fps
Recording Schedule	Schedule recordings through Continuous, Motion, Smart Motion (Person, Vehicle and Face), Alarm, Day, Hour per channel

Back-up File Format	DAV/ASF/AVI/MP4
Video Compression	H.265/H.264

#### Playback

Simultaneous Playback	Up to 4 channels, synchronized
Playback Speed	Variable Max 8x
Search	By Time/Date, All Motion Events or Smart Motion (Person/Vehicle/Face <sup>6</sup> ), Area Search

#### Storage

Hard Drive Bays	1 Bay
Hard Drive Capacity	Up to 8TB (SATA)
Backup Media	USB Flash Drive & USB HDD

#### Special Features

Smart Motion Detection Support	Yes for Person and Vehicle detection <sup>5</sup>
Wired/Wireless Fusion support	Yes <sup>3</sup>
Lorex Sensor Compatible	Yes <sup>3</sup>

Face Detection Support	Yes <sup>5</sup>
Mask Detection Support	Yes <sup>5</sup>
Package Detection (Missing Package and Package Left Behind):	Yes <sup>5</sup>
Animal Detection	Yes <sup>5</sup>
Smart Security Lighting™ Support	Yes <sup>5</sup>
Active Deterrence Support	Yes <sup>5</sup>
Active View Support	Yes <sup>5</sup>
Selectable Siren Support	Yes <sup>5</sup>
Panic Button	Yes <sup>5</sup>
Smart Search	Yes

#### Smart Home<sup>4</sup>

Voice Control	Amazon Alexa™, Google Assistant™
Streaming Options	Chromecast™, Apple TV™, Amazon Echo Show™, Google Home Hub™

#### Connectivity

Mobile Viewing	Android, iOS
Compatible APP	Lorex Home™
PC/Mac Remote Viewing	Yes/Lorex Cloud™ client
Email Notification	Text and Snapshot
Network Interface	10/100 Base-TX, RJ45
Network Bit Rate	80Mbps total, 48~8192kbps per camera
DDNS	Yes (Optional)
USB interface	USB 2.0 x 2

#### Additional Specifications

FW Upgrade	USB/Network
Watchdog Function	Yes
Power Consumption	Approx. 8.3W (HDD excl.)
Supply Voltage	100VAC-240VAC, 50/60hz, DC 53V/1.8A
Total PoE Power Output	PoE: Max 25.5W for single port, 72W total
Unit Dimensions (W x D x H)	12.9 x 9.6 x 2.1" / 328 x 245 x 53 mm
Unit Weight	2.75 lbs. / 1.26 kg (excl. HDD)
Operating Temperature	14° ~ 131°F / -10° ~ 50°C
Humidity	10 ~ 90% RH

# LOREX<sup>®</sup> Fusion 4K Network Video Recorder

## Model Information

N847A62    16-Camera Capable (8 Wired + 8 Lorex Fusion Wi-Fi) Fusion 4K Wired NVR with 2TB HDD    6-95529-05220-5

## Dimensions

Package	Plain Box
Package Weight	6.04lb / 2.72kg
Package Dimensions (W x D x H)	15.4 x 13.1 x 5.3" / 391 x 332 x 134mm
Package Cube	0.64cbf / 0.018cbm

## Back Panel



## What's in the box



1 x Fusion 4K NVR



1 x Ethernet cable



1 x Power Adapter



1 x HDMI Cable



1 x USB Mouse



Quick Setup Guide

### Disclaimers:

- 4K (8MP) IP cameras are required to take advantage of 4K recording.
  - Recording time may vary based on recording resolution and quality, lighting conditions and movement in the scene.
  - Lorex Fusion supports compatible Lorex wired cameras and Wi-Fi devices with sufficient signal strength between the Wi-Fi devices and your Wi-Fi router. All cameras must be connected to the same network. For full details on Wi-Fi cameras compatibility and instructions, visit [www.lorex.com/pages/fusion](http://www.lorex.com/pages/fusion)
  - Controlling certain features in your security system requires a compatible smart device. Availability and performance of certain features and services are smart device dependent and may not be available in all areas or networks. For compatibility, features, and instructions visit [www.lorex.com/smarthome](http://www.lorex.com/smarthome)
  - Compatible with certain Lorex IP and select wireless cameras only. For a list of compatible cameras please visit [www.lorex.com/compatibility](http://www.lorex.com/compatibility)
  - Accessing your security system remotely requires a high-speed Internet connection. Ensure your NVR has a wired connection to a router (not included). A minimum upload speed of 6Mbps is recommended for reasonable video performance.
  - HDMI output supports 4K HD for high definition multi-channel live or recorded video viewing. Image quality and resolution is dependent on the type of camera connected to the NVR, as well as TV/monitor resolution.
- \* Detection types need to be supported by the camera.

Lorex products are designed for consumer and business use only and not for US federal governments, federally-funded projects or contractors subject to NDAA.

All trademarks belong to their respective owners. No claim is made to the exclusive right to use the trademarks listed, other than the trademarks owned by Lorex Corporation. We reserve the right to change models, configurations or specifications without notice or liability. Product may not be exactly as shown.

Apple, the Apple logo and AppleTV are trademarks of Apple Inc., registered in the U.S. and other countries. App Store is a service mark of Apple Inc.

Google, Google Home, Google Play, Google Play logo, Google Assistant logo and Chromecast are trademarks of Google Inc.

Amazon, Alexa and all related logos are trademarks of Amazon.com, Inc. or its affiliates.

N847 Fusion Series NVR  
lorex.com

Lorex Corporation  
10440 Little Patuxent Parkway, Ste. 300,  
Columbia, MD 21044, United States

© 2023 Lorex Corporation

As our product is subject to continuous improvement, Lorex Technology & subsidiaries reserve the right to modify product design, specifications & prices without notice and without incurring any obligation. E&OE. (23-0050-LOR) 06022023-1