



Universal AC Laptop Charger - 65 W

Power Adapter with Nine Plug Tips and Universal Voltage, Compatible with Most Notebooks, Ideal as Replacement Power Supply, Includes Detachable AC US Power Cable, Black

Part No.: [180979](#)

EAN-13: 0766623180979 | UPC: 766623180979

Laptop Power Adapter as Your Reliable Companion for Home, Office and Travel

Designed to be the perfect secondary power adapter for your AC-powered notebook, the Manhattan laptop charger is versatile enough to keep at home, stow in your travel bag, or serve as a replacement for a lost power supply. Delivering up to 65 W of dependable power, it ensures your device remains charged and ready for action no matter where you are.

Maximum Compatibility

Thanks to its intelligent technology, this charger automatically adapts to five different voltage output levels (15, 18.5, 19, 19.5, and 20 V). It provides a comprehensive mobile power solution for a wide range of laptops, Chromebooks™, and Ultrabooks™ from leading brands such as Acer®, Asus®, Dell®, HP®, Lenovo®, Sony® and many more. The charger features a detachable 1.5 m (5 ft.) power cord with a C7 to AC wall plug, along with a built-in 1.2 m (4 ft.) power cord equipped with nine convertible plug tips, ensuring proper polarization and fit. The included detachable AC power cable allows for use as a travel adapter. Simply swap out the included C7 to US cable for other plugs like EU or UK, and you're all set.

Uncompromising Safety

Safety is our utmost priority. That's why our Universal AC Laptop Charger is equipped with overload, overcurrent, and overheating protection, providing you with peace of mind.

Features:

- Pocket-friendly charger, ideal as second or replacement power adapter delivering up to 65 W for your AC powered notebook
- Automatically selects among five voltage output levels (15, 18.5, 19, 19.5 and 20 V) for a broad mobile power solution
- Detachable 5 ft. (1.5 m) power cord with C7 to AC wall plug
- Built-in 4 ft. (1.2 m) power cord with nine convertible plug tips ensure proper polarization and fit
- Compatible with most laptops, Chromebooks™ and Ultrabooks™ from Acer®, Asus®, Dell®, Fujitsu®, HP®, Lenovo®, Medion®, Sony®, Samsung®, Toshiba® and more
- Overload, overcurrent and overheating protection
- Compact, portable and lightweight design for easy travel
- Detachable power cable that can be exchanged for different regional versions like C7 to US, EU, UK and more - no separate travel adapter needed
- Built-in cable tie to prevent tangling and keep cords neatly stored
- Three-year warranty

Specifications:

Standards and Certifications

- CE
- RoHS
- REACH
- ETL
- FCC
- UKCA

Electrical

- AC input: 110.0 - 240.0 V; 50 - 60 Hz, 1.5 A (max.)
- Voltage/current settings (maximum):
 - 65.0 W output:
 - 15.0 V / 4.0 A
 - 18.5 V / 3.51 A
 - 19.0 V / 3.42 A
 - 19.5 V / 3.33 A
 - 20.0 V / 3.25 A
- Overshoot voltage: ≤5%
- Ripple and noise: ≤200.0 mV

Included DC plug tips - formats

- M1: Ø 6.0 x 3.0 x 10.7 mm (15.0 V)
- M4: Ø 4.8 x 1.7 x 10.7 mm (18.5 V)

- M5: Ø 5.5 x 2.5 x 10.7 mm (19.0 V)
- M7: Ø 5.5 x 2.1 x 10.7 mm (19.0 V)
- M8: Ø 6.0 x 4.5 x 10.7 mm (19.5 V)
- M11: Ø 7.9 x 5.5 x 12.5 mm (20 V)
- M13: Ø 5.5 x 1.7 x 10.7 mm (19.0 V)
- M20: Ø 4.0 x 1.7 x 10.7 mm (19.0 V)
- M28: 11.0 x 4.6 x 12.0 mm (20.0 V)

Protection Characteristics

- Short-circuit (SCP) with auto-recovery mode
- Overvoltage (OVP) with auto-recovery mode
- Overcurrent (OCP) — current limit: 150% (max)
- Over-temperature (OTP)

Physical

- Dimensions (L x W x H): 4.33 x 1.89 x 1.18 in. (110 x 48 x 30 mm)
- Net weight: 0.75 lbs. (340 g)
- Gross weight: 0.88 lbs. (400 g)
- Housing: plastic

Operating Environment

- Operation temperature: 32 - 77°F (0 - 30°C)
- Storage temperature: -4 - 185°F (-20 - 65°C)
- Operation humidity (noncondensing): 20 - 80%
- Storage humidity (noncondensing): 10 - 90%

Package Contents

- Universal AC Laptop Charger 65 W - US
- Detachable 1.5 m (5 ft.) power cord with C7 to AC wall plug
- Built-in power cord, 1.2 m (4 ft.) for DC tips
- 9 interchangeable DC tips
- Instructions

Compatibility

- NOTE: Please check your current charger's output and voltage to ensure compatibility with the above-mentioned electrical requirements
- Compatible devices include but are not limited to: Acer®, Asus®, Compaq®, Dell®, Fujitsu®, HP®, Lenovo®, Medion®, Sony®, Samsung®, Toshiba® and more

